

# QUARK PMM Series Process Multimeters



	PMM440A/D	PMM330A/D
<b>Current (measure)</b>	0-100uA; 0-1mA; 0-10mA; 0-100mA	0-10mA; 0-20mA; 4-20mA; 10-50mA
<b>Current (generate)</b>	0-100uA; 0-1mA; 0-10mA; 0-100mA	0-10mA; 0-20mA; 4-20mA; 10-50mA
<b>Voltage (measure)</b>	0-100mV; 0-1V; 0-10V; 0-100V	0-1V; 0-100V; 0.25-1.25V; 1-5V
<b>Voltage (generate)</b>	0-100mV; 0-1V; 0-10V; 0-25V	0-1V; 0-25V; 0.25-1.25V; 1-5V
<b>2 wire transmitter</b>	0-100uA; 0-1mA; 0-10mA; 0-100mA	0-10mA; 0-20mA; 4-20mA; 10-50mA
<b>Display</b>	Engineering Units	Process Percentages

The Quark PMM Series Process Multimeters are unique instruments for the generation and measurement of common industrial current and voltage signals.

- 4 models to cover most applications
- 0.1% resolution of selected range
- readings in engineering units or process percentages
- signal regeneration by potentiometers or touch buttons
- integral rechargeable battery giving 12 hours operation
- 8 hours full recharge time

All models are supplied 'ready to go' with mains/charging leads and leather carrying case.



sales, hire, calibration and repair of industrial instrumentation

Instrument House  
Morgan Drive  
Guisborough  
Cleveland  
TS14 7DG

E-mail [sales@euremica.com](mailto:sales@euremica.com)  
Website [www.euremica.com](http://www.euremica.com)

Telephone 01287 20 40 20  
Facsimile 01287 20 40 21